

BXL1800

Technical Specifications

GB

Version 1.1 December 2005



ULTRABASS

www.behringer.com



ULTRABASS

180-Watt 2-Channel Bass Workstation with Original BUGERA™ 12" Speaker, FBQ Spectrum Analyzer, Compressor and Ultrabass Processor

- ▲ Powerful 180-Watt 2-channel Bass Workstation in wedge-shaped cabinet
- ▲ Original BUGERA™ 12" special high-impact cone speaker
- ▲ Clean channel with dedicated Gain control
- ▲ Distortion channel with dedicated Gain, Shape and Level controls
- ▲ Ultra-musical, active 7-band graphic EQ with FBQ Spectrum Analyzer
- ▲ Revolutionary “See what you play” FBQ frequency indicator for instant sound shaping
- ▲ Switchable Ultrabass subharmonics processor for unbelievable low-end power
- ▲ Integrated Compressor smoothens out volume peaks when playing dynamic slaps
- ▲ Musical opto-limiter for ultimate volume without distortion
- ▲ Dual footswitch for Channel select and Ultrabass function included
- ▲ Separate headphone output—perfect for quiet practicing
- ▲ Balanced XLR DI and line outputs for direct connection to your mixing console
- ▲ CD input allows you to play along to your favorite music
- ▲ Dedicated FX Insert for external effects devices (stomp boxes, rack effects, etc.)
- ▲ High-quality components and exceptionally rugged construction ensure long life
- ▲ Conceived and designed by BEHRINGER Germany

BXL1800

SPECIFICATIONS

	BXL1800
AUDIO INPUTS	
Instrument input	¼" TS
Input impedance	250 kOhm
CD input	RCA
Input impedance	40 kOhm
FX INSERT RETURN	¼" TS
Input impedance	50 kOhm
AUDIO OUTPUTS	
Phones Out	¼" TRS stereo
Direct Out	XLR
Output impedance	500 Ohm
Line Out	¼" TS
Output impedance	100 Ohm
FX INSERT SEND	¼" TS
Output impedance	2.2 kOhm
SYSTEM SPECIFICATIONS	
Power amp output	180 W @ 4 Ohm
LOUDSPEAKERS	
Type	12"
Impedance	BUGERA™ Classic Tone Series
Model	4 Ohm
Power handling	120 W
POWER SUPPLY	
Mains voltage	USA/Canada 120 V~, 60 Hz
	Europe/U.K./Australia 230 V~, 50 Hz
	Japan 100 V~, 50 - 60 Hz
	China/Korea 220 V~, 50 Hz
	General export model 120/230 V~, 50 - 60 Hz
Power consumption	max. 290 Watt
Fuses 100 - 120 V~	T 6.3 A H 250 V
Fuses 200 - 240 V~	T 3.15 A H 250 V
Mains connection	Standard IEC receptacle
DIMENSIONS/WEIGHT	
Dimensions (H x W x D)	522 x 413 x 419 mm
	20.6" x 16.3" x 16.5"
Weight	21.55 kg
	47.5 lbs

BEHRINGER is constantly striving to maintain the highest professional standards. As a result of these efforts, modifications may be made from time to time to existing products without prior notice. Specifications and appearance may differ from those listed or illustrated.

Technical specifications and appearance subject to change without notice. The information contained herein is correct at the time of printing. The names of companies, institutions or publications pictured or mentioned and their respective logos are registered trademarks of their respective owners. Their use neither constitutes a claim of the trademarks by BEHRINGER® nor affiliation of the trademark owners with BEHRINGER®. BEHRINGER® accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colours and specification may vary slightly from product. Products are sold through our authorised dealers only. Distributors and dealers are not agents of BEHRINGER® and have absolutely no authority to bind BEHRINGER® by any express or implied undertaking or representation. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of BEHRINGER Spezielle Studiotechnik GmbH. BEHRINGER® is a registered trademark.

ALL RIGHTS RESERVED. © 2005 BEHRINGER Spezielle Studiotechnik GmbH,
Hanns-Martin-Schleyer-Str. 36-38, 47877 Willich-Münchheide II, Germany.
Tel. +49 2154 9206 0, Fax +49 2154 9206 4903